COMMANDER Business Landline

Welcome to Commander.

Business Landline

Thank you for choosing Commander to provide your business the fantastic benefits our service has to offer. This User Guide is designed to help you make the most of your new business landline service and includes handy hints for setting up your network. This guide also features important numbers you can contact if you require further assistance.

MY ACCOUNT NUMBER:

Note: if your business lines are connected to a Phone System or PBX, please refer to the manufacturer user manual for instructions

This guide is not applicable to Commander mobile features, IP Voice or to services over the nbn. Monthly or per usage charges may apply for some of these features. Look for the following symbols: (\$) (\$)

See the Critical Information Summary for your plan for information on relevant charges: commander.com.au/legal/critical-information-summaries. Visit our website for full lists of rates and charges: commander.com.au/legal/customer terms. Available on most tone phones and in most areas.

Contents.

	64	CALL OPTIONS	
600000000000000000000000000000000000000	888	Call Waiting	8
SERVICES	്പം	Return	10
Phone COCCCCC	699	Forward	<u> </u>
	6 ČČ		<u> </u>
Mobile	6ČČ	Busy	12
Electricity		No Answer	13
Bundles	700	Selected Callers	14
nbn		Set Time	16
		Multiple Numbers	19
		MessageBank®	20
		SMARTER CALLS	
		3-way Chat	26
		Call Back	27

FASTER DIALLIN	G 28
Delayed Hotline	28
Abbreviated Dialling	g 29 -
5868686868	<u> </u>
WHO'S CALLING	? 30
Call Number Displa	y 30 C
Hide Your Number	33
MANAGE CALLS	34
Call Control	34
Remote Access	35
PIN COCCOCCO	36
HANDY NUMBER	S 37

Take Command.

Manage your account

Take control of your communications with Take Command – your free online account management tool. To view your account details, payment history and make changes to your account, visit **takecommand.com.au**. Registration details will be sent to your nominated email address separately.

Commander is so much more than just phones.

Commander is a true one-stop shop for business, with a full suite of telco, data and power to help businesses stay connected.



PHONE

Commander has a range of business phone products and plans, from a smart office phone to a complete hosted internet phone system, and can help you tailor the right phone system to suit your business.



INTERNET

With a large range of broadband and internet services available to businesses, you can choose the amount of data you need, the option of faster connection or to add a phone bundle to your plan.



MOBILE

We have an array of mobile phones to choose from and competitive mobile plans to match. Our data plans are created to suit every business size or needs.



ELECTRICITY

We have electricity available in Victoria, South Australia and New South Wales. It's all the same power supply, but if you switch to Commander Electricity you'll get 20% of our market usage rates when you pay on time. Energy Price Fact Sheets are available at <u>commander.com.au/pfs</u> and excludes certain locations and meter configurations.



BUNDLES

It's simple. By bundling your phone and internet or your phone and electricity together and paying on time, you get even more savings for your business.



NBN™

The nbn will revolutionise the way you do business with faster connections and consistent speeds. Our nbn specialists can assist and guide you through every step of the way in your transition to the nbn.

Never miss an important call again.

Call waiting

If you receive a call whilst you're already on the phone, Call Waiting can ensure you don't miss any other calls. While you are on a call, you will hear a subtle 'beeping' tone every few seconds if someone else is trying to call you. To switch calls, simply put the first caller on hold while you answer the second call. You can also switch between calls as often as you like. Plus, there is no need to switch Call Waiting 'ON' as it is set up automatically as part of most Commander phone services.

How does it work?

Answer an incoming call / switch between co	Ils (RECALL) DIALTONE 2
Hang up one call and return to the other	(RECALL) DIAL TONE 1
Reject an incoming call	(RECALL) DIAL TONE 0
Turn ON Call Waiting	() DIALTONE * 4 3 # ANNOUNCEMENT
Turn OFF Call Waiting	(DIALTONE # 43 # ANNOUNCEMENT

Useful info.

Once you have switched Call Waiting ON, it will stay ON unless you turn it OFF. It's also important to note that Call Waiting won't work during a 3-Way Chat call.

With some fax machines and dial-up modems the 'beeps' on Call Waiting can

Call return

Call Return quickly lets you find out who's call you missed (this doesn't work for blocked numbers).

How does it work?

Retrieve the number of last unanswered call

To call the number back

Useful info.

Call Return is already set up and ready to use (for tone phones most areas of Australia) There is a per use charge (s) for Call Return and call charges also apply if you return the call.

Call forward

Call Forward helps you manage calls by forwarding them to another destination when certain criteria are met. For example, when you are busy on another call or don't answer the phone, you may want to forward calls to your assistant using your Call Forward settings.

Call forward immediate

With Call Forward Immediate, all calls to your primary phone are redirected to a number you choose.

How does it work?

★ 10 #

Turn ON Call Forward Immediate for incoming calls

() * 2 1 Phone number #

Turn OFF Call Forward Immediate for incomina calls

Call forward busy

When someone calls and your phone is engaged, the caller will be forwarded to another number that you have chosen.

How does it work?

Turn ON Call Forward Busy for incoming calls

Turn OFF Call Forward Busy for incoming calls

Check if Call Forward Busy is ON/OFF

Call forward no answer

If there is no one to answer your phone, your calls can be sent onto a number where there is someone available. Although the phone comes with a default 'no answer' delay of 20 seconds (around seven rings) you can set the delay from 5 to 55 seconds.

How does it work?

Turn ON Call Forward No Answer for incoming calls

(𝔅) ★ 6 1 Phone number #
 (𝔅) ★ 6 1 Phone number ★

() * 6 1 # ANNOUNCEMENT

Time in seconds (#)

() **#** 6 1 **#**

Change time delay (in seconds) before call forward

Turn OFF Call Forward No Answer for incoming calls

Check if Call Forward No Answer is ON/OFF

Useful info.

Call Forward Immediate, Call Forward Busy and Call Forward No Answer are already set up and ready to use. Calls may not be forwarded to some numbers, including international numbers and 000. Call charges apply for the calls you forward (§).

Call forward selected callers

You can create a 'Selected Callers List' of up to 15 numbers that can be forwarded to another phone. To get this service connected, call Commander on **132 777**.

How does it work?

Turn ON Call Forward Selected Callers

Turn OFF Call Forward Selected Callers

Check Call Forward Selected Callers is ON/OFF

(* * 92#) (* # 92#) (* * # 92#) (* * # 92#)

ected Callers is ON/OFF

Useful info.

All other Call Forwards are overridden by Call Forward Selected Callers. You will need to activate your PIN on your business phone to use this service. Calls may not be forwarded to some numbers, including international numbers and 000. Call charges apply for the calls you forward (§).

HOW TO MANAGE YOUR SELECTED CALLERS LIST

Add number to your 'Selected List' (* * 3 (7) PIN * ANNOUNCEMENT 4 * ANNOUNCEMENT List position * ANNOUNCEMENT Caller's phone number * ANNOUNCEMENT Forwarding destination phone number # ANNOUNCEMENT

Check which position a number is on 'Selected Callers List' (*#87 PIN * ANNOUNCEMENT 4* ANNOUNCEMENT List position # ANNOUNCEMENT

Remove number from your 'Selected List'

() #87 PIN * ANNOUNCEMENT 4* ANNOUNCEMENT 1 ANNOUNCEMENT
List position # ANNOUNCEMENT



Call forward set the time

Get your calls to follow you by setting up different forwarding instructions for up to 15 different time periods. You can specify the day, the times and a replacement phone number for all your incoming calls during each 'window'.

To get this service connected, call Commander on 132 777.

How does it work?

Turn ON Call Forward Set the Time

Turn OFF Call Forward Set the Time

Check Call Forward Set the Time is ON/OFF

Create/modify 'Time Period List'

(*16#)
(*16#)

() * # 16 # ANNOUNCEMENT () * 87 PIN * ANNOUNCEMENT 9 *

(ANNOUNCEMENT) List position * ANNOUNCEMENT Start day number * Start time ANNOUNCEMENT Finishing day number * Finishing time ANNOUNCEMENT Forwarding Destination number * ANNOUNCEMENT Check destination number and () * # 8 7 PIN * ANNOUNCEMENT 9 * ANNOUNCEMENT List position # ANNOUNCEMENT times for 'Time Period List' entry () # 8 7 PIN * ANNOUNCEMENT 9 * ANNOUNCEMENT Remove setting from ANNOUNCEMENT List position # ANNOUNCEMENT Time Period List Remove all numbers from Time Period List ANNOUNCEMENT 1 # ANNOUNCEMENT Day numbers Monday 1, Tuesday 2, Wednesday 3, Thursday 4, Friday 5, Saturday 6, Sunday 7 24-hour mode (eq 7.30am = 0730, 7.15pm = 1915) Times Useful info. to activate your PIN on your business phone to use this service. Calls may not be



Multiple numbers

You can add an extra phone number to your existing business phone line (this feature allows you to have a separate ring tone, so you know which line is calling). To set up Multiple Number, call Commander on 132 777.

How does it work?

Call charges will default to your primary number. However, if you want to use Call Return, Call Forwarding or Call Control on your second number, simply enter the prefix (*112) # first.

Useful info.

For long distance calls you will need to pre-select Commander for both your basic phone service (prime number) and your auxiliary number. You will also need a phone with distinctive ring capability.

You can use Remote Access to change your Call Forwarding and Call Control settings on the second number (see How to manage your calls section for more details).

Call Waiting and Call Back will still work if you have Multiple Number. Calling Number Display will also work, but you won't know which of your numbers was called. A monthly charge applies ().

MessageBank®

When you are on another call or can't answer your phone, the caller can leave a message on your phone.

To activate your MessageBank service, please call Commander on **132 777**. Monthly charges apply to activate MessageBank (\$).

How does it work?

When you first call your MessageBank service, you will get a voice prompt that will guide you through the process of recording your personal greeting and setting up a PIN.

You then simply follow the prompts to set up your mailbox.

You won't need to enter your PIN when you call your MessageBank from your business phone, however you will need it if you are calling from another fixed or mobile service.

ACCESSING MESSAGEBANK

Access from phone it's connected to

Access from another fixed/mobile phone within Australia

101 or 125101 and, if prompted, MessageBank PIN #

125102 and, when prompted, Mailbox number # and MessageBank PIN # (Mailbox no is your phone number incl. area code)

Access from services connected to some PABXs/other carriers

Call 1800 135 102

Access from phone services in other countries

Call +61 418 707 102 followed by 125102, Mailbox number # MessageBank PIN #

MessageBank is a registered trademark of Telstra.

CHANGING YOUR PIN & GREETING

If you prefer the added security of PIN protection when calling MessageBank from your business phone, you can change your PIN at any time by accessing the settings.

Access Main Menu	Call MessageBank 9
Set Up menu	3
PIN Change menu	3
Change the PIN	1 or for Security Settings 1, 2
Turn OFF Optional PIN	1

When Optional PIN is ON, enter your PIN to call MessageBank. When the Optional PIN is OFF, enter PIN only when calling MessageBank from another fixed phone/mobile.

MANAGING YOUR MESSAGES

As soon as you pick up your phone, you will know that you have new messages because you'll hear a special 'interrupted' dial tone. It's also possible to get a text message sent to your mobile whenever someone leaves you a new message.

125101, 4, follow prompts

Turn ON SMS Message Notifications

Useful info.

If you are using a dial-up internet service, make sure that you clear your MessageBank messages first, or the 'interrupted dial tone' may not be recognised by your modem.

LISTENING TO YOUR MESSAGES

When you call MessageBank, your messages will play automatically.

After listening to your messages, you may select from the following options:

Replay message	1
Return the call	22
Delete & go to next message	5

STORING YOUR MESSAGES

MessageBank will automatically store new messages for 14 days, and for 7 days once played (unless deleted). There is storage for up to 60 messages (up to 5 minutes each).

SEE WHO CALLED WITHOUT LEAVING A MESSAGE

If a caller listens to your greeting but doesn't leave a message, you can still access their number (up to 5 unless blocked).

Turn ON

9, 3, 5, 6 Select ON

HOW TO CHANGE THE TIME BEFORE MESSAGEBANK ANSWERS THE CALL

Unanswered calls are forwarded to your MessageBank after 20 seconds (approx. 7 rings), and can be changed anywhere from 5 -55 seconds.

Change the time before call is forwarded

🖉 \star 🤊 🔋 Time in seconds #

Useful info.

MessageBank is available in most areas around Australia. A monthly access charge applies (3), If you are already connected to MessageBank, but need assistance you can call Commander on **132** 777.

MessageBank Shortcuts

WHEN USING MESSAGEBANK Go to Main Menu Cancel and go back one menu level

ancer and go back one men

Get Help

9 * 8

WHEN LISTENING TO YOUR MESSAGES
Go back to the start of the message
Go back 8 seconds
Go forward 8 seconds
Fast forward to the end of the message
Skip to the next message
Pause a message while it is playing
& to resume playing message

Smarter ways to call.

3-way chat

With 3-Way Chat, you can add another person if you're already on a call. You can talk to two people at once, and either person can leave the call at any stage, so you can bring in another caller.

RECALL

How does it work?

Put caller on hold & make new call

Bring both callers into a 3-Way Chat

Split a 3-Way Chat (this will put one call on hold)

Switch between calls

Hang up one call & return to caller on hold

Useful info.

3-Way Chat is already set up on your phone, ready to use. Call Waiting won't work while on a 3-Way Chat, but Call Forward Immediate or Busy works if you have them set up.

A per use charge for 3-Way Chat applies (§). Call charges apply at standard rates for each call that joins the chat.

DIALTONE Phone number RECALL DIALTONE 3 RECALL DIALTONE 2 RECALL DIALTONE 2 RECALL DIALTONE 2 RECALL DIALTONE 1

Call back

If you call a busy number, you don't have to wait around to try again. By setting Call Back, our system will recognise when the number you want is available and call you back automatically . You can 'watch' up to five different numbers at the same time.

How does it work on most phones?

Set up a Call Back	BUSY TONE (RECALL) * 37 # ANNOUNCEMENT
Cancel a Call Back	<i>(</i> #37#)
Check for an active Call Back	() * # 37 # ANNOUNCEMENT

Useful info.

Call Back is already set up on your phone and ready to use. The busy destination will be monitored for 45 minutes. Call Back will not work for all calls, including calls to Operator Assisted Services, some business numbers, international numbers and to phones on some other networks.

There is a maximum of five Call Back calls at any one time. You will need a tone phone (one with a distinctive ring capability is preferred).

A per use charge for Call Back and call charges apply (\$). Call charges apply at standard rates.

A faster way to dial.

Delayed hotline

Is there a number you frequently call? With the Delayed Hotline service, you don't even have to dial it to make the call. Simply pick up the phone, wait 4 seconds and it will automatically start calling. You have a 4-second window to give you time to start dialling a different number.

How does it work?

Turn ON Delayed Hotline

Turn OFF Delayed Hotline

Check if Delayed Hotline is ON/OFF

() * 53 Hotline number # () # 53 #

() * # 5 3 # ANNOUNCEMENT

Useful info.

The Delayed Hotline overrides Call Control, which means that you can use Delayed Hotline for a specific number and still have a block on making that type of call to other numbers. Check the How To Manage Your Calls section for details.

Please note you can't store 000 as a Hotline number. A monthly charge applies (s).

Try using Delayed Hotline with your MessageBank service, so you don't have to keep entering your mailbox access number.

Abbreviated dialling

If you call the same numbers often, Abbreviated Dialling can convert up to 8, 40, or 60 numbers into one or two digit speed dial codes, saving you remembering individual phone numbers (ideal for programming special service and long international numbers).

ABBREVIATED DIALLING - 8 NUMBER MEMORY

Store up to 8 numbers as one-digit codes (from keys 2 to 9): press the key to make call.

ABBREVIATED DIALLING - 40 OR 60 NUMBER MEMORY

Use two-digit codes (20 to 59 or 79) to store a lot of numbers. Call 132 777 to activate.

How does it work?

Call a stored number

Abbreviated code # eg 3 #

Enter/change stored number

(*) 5 1 Abbreviated code , Phone number (#)

Cancel a stored number

🖉 # 5 1 Abbreviated code #

Useful info.

(1) # cannot be used as an Abbreviated Code. A monthly charge applies (6). Abbreviated Dialling overrides Call Control, which means that you can use Abbreviated Dialling for a specific number and still have a block on making that type of call to other numbers. Check the How To Manage Your Calls section for details.

See who's calling.

Calling number display

Check who's calling (except blocked numbers) before you answer your phone by having the caller's number displayed on your phone display screen (you will need a phone with a display screen).

How does it work?

When your phone rings, simply look at your display screen to see the caller's number. Some phones, can be programmed with a limited selection of numbers and names. Your phone will then display the name from your list when they call you. Please note this is handset dependant (refer to your phone manufacturer's user manual for instructions).

If you can't answer your phone or don't recognise the number, you can store the number and return the call later. Storing or logging some numbers is a standard feature on most display phones. To activate Calling Number Display on your phone, call Commander on **132 777**.

THE CALLING NUMBER DISPLAY SCREEN

Calling Number Display needs a phone with a display screen.

WHY CALLING NUMBER DISPLAY MAY NOT ALWAYS WORK

- A silent line or unlisted number
- A caller who has blocked their number
- An overseas number
- Someone who's phone service provider or carrier doesn't participate in Calling Number Display or who needs their subscriber to activate number display
- A payphone

Useful info.

A monthly charge applies for Calling Number Display (3). Available on tone phones in most areas in Australia. Call Waiting Display capable phones are designed to mute the receiver for 1-2 seconds while the details of the caller's number are sent to the phone. This may cause a brief interruption to the conversation. Occasionally, some phones may mistakenly respond to a caller's voice or external noise causing a 'false muting'.

Call Waiting Display

Some display phones have Call Waiting Display, which will let you see the number of a second caller when you're already on the phone (unless that number is blocked).

Call Record Logging

Most phones that are compatible with Calling Number Display will also support call record logging. Capacity does vary so please check your phone manufacturer's user manual.

Hide your number CALL BLOCKING

Call Blocking is free and it gives you the option to block your number on an individual call. When you're calling from a Commander fixed phone, just add 1831 to the front of the number before you dial.

LINE BLOCKING

If you don't want your number to be sent when you make a call you can use Line Blocking. Permanent Line Blocking is automatically provided to customers with unlisted numbers and is available on request for listed services. You can also override the blocking on individual calls by adding 1832 to the front of a number when you dial from a Commander fixed phone.

How to manage your calls.

Call control

To manage your call costs or have control of who shares your phone, you can use Call Control to set various barring levels on certain outgoing call types, including International, national/STD, 190 or local calls.

Call 132 777 to set up Call Control.

How does it work?

Turn ON Call Control

Turn OFF Call Control

Check Call Control is ON/OFF

(* * 3 3 PIN # (* # 3 3 PIN # (* # 3 3 #) ANNOUNCEMENT

Useful info.

A monthly charge applies ③, Reverse Charge calls can still be received. You will need to activate your PIN on your business phone before you can use Call Control.

Remote access

You can change your Call Waiting, Call Forwarding, Call Control and Delayed Hotline settings without being at work. Using Remote Access, you can quickly change your Call Forward settings.

How does it work?

Example: Turn ON Call Forward Immediate with Remote Access C Access number ANNOUNCEMENT Your number * PIN * ANNOUNCEMENT * 21 Phone number # ANNOUNCEMENT

Useful info.

You will need to activate your PIN on your business phone before you can use Remote Access. Only one change can be made per Remote Access call. To connect Call Control or Delayed Hotline, call Commander on **132 777**. Applicable call costs and a monthly charge apply (3).

Personal identification number (PIN)

For your security you will need a personal identification number or 'PIN' to activate, use or change your settings for Call Control, Call Forward Set The Time, Call Forward Selected Callers and Remote access. You can use the same PIN for all of these services.

To set up your PIN, call Commander on 132 777.

How does it work?

When you initially set up your PIN you will get a temporary PIN, which will be the last four digits of your phone number. You will then need to activate your PIN from your business phone.

You can change your PIN as many times as you like, however, when you reset your PIN, you need to call from a phone service that has business features on it.

If you lose or forget your PIN, call Commander on 132 777.

Change your PIN (* 30 Old PIN * New PIN * New PIN # ANNOUNCEMENT

Handy numbers

CUSTOMER SERVICE & ACCOUNT ENQUIRIES 132 777 ACCOUNT MANAGER 1300 123 900 LOCAL COMMANDER CENTRE 1300 132 777

Commander Customer Care 132 777

🕑 www.commander.com.au



© Copyright M2 Commander Pty Ltd. All rights reserved. ABN 85 136 950 082.