



Changing the Commander E-PBX Time and Date

Set Time and Date:

Programming to be done on main station (port 101 or 102)

- > Dial *95
- > Dial user 23646 Press ✓
- > Enter password 23646 Press ✓
- > Dial (time) 12 Press ✓
- > Enter time (hh:mm)24hours 1645 Press ✓
- > Press ⇨ Press ✓ + ✓
- > Enter Date (231003) 231003 Press ✓
- > Press Service Key Exit programming